



Expands the CM-30 in increments of 30 lines

Each CMX-300 provides an additional 30 lines to the basic 30 lines provided by the CM-30. You may add up to two Model CMX-300s which will allow you to monitor up to a total of 90 lines. All the standard features of the CM-30 are maintained when using the CMX-300.

Installation is easy.

You can add the CMX-300 to an existing installation without disconnecting the service of the CM-30. The CMX-300 is installed with the CM-30, simply connect the lines you want to monitor and you're ready to start.

No extra power supply unit is required. The CMX-300 gets its power from the CM-30.

Benefits

- 30 line capacity
- Expands the CM-30 in increments of 30 lines per unit up to 90 lines
- Compatible with analog Centrex, PBX or Key System lines
- Connectorized interface
- Can be wall mounted

Application

When your system needs to grow beyond the 30 line capacity of the CM-30, you can expand quickly and efficiently with the CMX-300. It will allow you to expand your system in increments of 30 lines per unit. Up to two CMX-300 units can be added to any CM-30 providing monitoring capabilities of up to 90 lines. If the size of your organization already exceeds the 30 line limitation set by the CM-30, the combination of the CM-30 and CMX-300 is your solution.

Specifications

	Min	Typical	Max	Unit
Breakdown Volts				
Observed lines to ground			1000	VDC
Environmental				
Operating Temperature	32		122	°F
	0		50	°C
Humidity (non-condensing)			95%	RH

Ordering Information

CMX-300 Service Observing Expander

Certification

DOC CS03
 CSA C22.2 No. 225-M90
 FCC Part 68
 UL 1459-2

Approval Number

350 3518 A
 LR 91817
 FCNCAN-61252-PX-N
 D0292442DBC

Connections

Two A25B or equivalent 25 pr. connector cables

Mounting

Apparatus cabinet, relay rack, or backboard

Dimensions (LxWxH)

9.25" x 5.40" x 1.58" (23.5 cm x 13.7 cm x 4 cm)

Shipping Weight

1.9 lbs. (0.86 kg)

